

COMMANDS DEFINE TABLE

Command	Camera Feedback
#100#0#	Mode:Camera
#100#1#	Mode:Video
#100#2#	Mode:Dual
#101#3#	Image Size:3M
#101#8#	Image Size:8M
#101#16#	Image Size:16M
#106#360#	Video Size:640X360
#106#720#	Video Size:1280X720
#120#1234567890#	1234567890 added !
#121#1234567890#	1234567890 deleted !
#130#sales@cedo.cn#	sales@cedo.cn added !
#131#sales@cedo.cn#	sales@cedo.cn deleted !
#135#	Camera Wake : On !
#136#	Camera Sleep : On !
#145#	GPS Location:E89N89
#150#	Image send enable
#160#	Image send disable
#165#1#	Daily Report : On!
#165#0#	Daily Report : Off!
#180#	Wireless ON !
#181#	Wireless OFF !
#185#1#	Wireless: MMS
#185#2#	Wireless: SMTP
#185#3#	Wireless: FTP
#190#mmsc.monternet.com#	MMS URL : mmsc.monternet.com
#191#10.0.0.172#	MMS IP :10.0.0.172
#192#80#	MMS PORT : 80
#195#cmwap#	GPRS APN : cmwap
#196#2#	GPRS Account : 2
#197#3#	GPRS Password : 3
#200#1#	SMTP Server : 1
#201#2#	SMTP Server Port : 2
#202#3#	SMTP email : 3
#203#xxx#	SMTP Password:xxx
#204#1#	SMTP: SSL
#204#2#	SMTP: NOT SSL
#210#1#	thumbnial size:320X240
#210#2#	thumbnial size:640X480
#210#3#	thumbnial size:1280X720
#210#4#	thumbnial size:1280X960
#210#5#	thumbnial size:1920X1080
#210#6#	thumbnial size:2048X1536
#210#7#	thumbnial size:2560X1920
#211#xxx#	Daily Max: xxx
ANY MISTAKE	Invalid command !

Remark:

- * When you send a text message, the camera will not execute the command if the camera is in standby mode.
- * When the camera is activated (some movement within the range), the camera will wake up and start executing commands.
- *When you send a text message, the camera will immediately execute the command if the camera is triggered at this moment.